

MAX20472

Low-Voltage Synchronous Boost Converter

Industry's Only Automotive Synchronous Boost Converter with Up to 1A of Output Current and True Shutdown and Active-Low RESET Output



NDA Required. [Request Full Data Sheet and Software](#)

Description

Create a design and simulate using EE-Sim® tools: [MAX20472](#)

The MAX20471, MAX20472, and MAX20473 are high-efficiency, low-voltage DC-DC converters that boost a 3.0V to 4.0V input supply to between 3.8V and 5.25V (factory configurable) at 500mA, 1A, or 2A. The boost converters achieve $\pm 1.5\%$ output error over load, line, and temperature ranges.

The ICs feature a 2.2MHz fixed-frequency, forced pulse-width modulation (FPWM) mode for better noise immunity and load-transient response, as well as a pulse-frequency modulation (skip) mode for increased efficiency during light-load operation. The 2.2MHz frequency operation enables the use of all-ceramic capacitors and minimizes external components. The programmable spread-spectrum frequency modulation minimizes radiated electromagnetic emissions. Integrated low $R_{DS(ON)}$ switches improve efficiency at heavy loads, which make the layout a much simpler task with respect to discrete solutions.

Other features of the parts include true output shutdown, soft-start ramping, overcurrent limiting, and overtemperature protection.

Key Features

- Synchronous Boost Converter
 - 3.8V to 5.25V Output in 50mV Steps
 - 500mA, 1A, and 2A Output Versions
- 3.0V to 4.0V Operating Supply Voltage
- True Output Shutdown
- 2.2MHz Switching Operation
- Open-Drain Reset Output Pin (Active-Low RESET)
- Spread-Spectrum Enable Pin (EN)

- High Precision
 - $\pm 1.5\%$ Output-Voltage Accuracy
 - $93V \pm 2\%$ Undervoltage Monitoring
 - $107V \pm 2\%$ Overvoltage Monitoring
 - Good Load-Transient Performance
- Robust for the Automotive Environment
 - Current-Mode Control, Forced-PWM, and Skip Operation
 - Overtemperature and Overcurrent Protection
 - 12-Pin (3mm \times 3mm) TDFN
 - 8-Pin (0.150") SOIC (MAX20471 Only)
 - $-40^{\circ}C$ to $+125^{\circ}C$ Automotive Temperature Range

Applications/Uses

- Automotive CAN Transceivers
- Automotive Point of Load

Part Number	V_{IN} (V)		V_{OUT1} (V)		Preset V_{OUT} (V)	I_{OUT1} (A)	Output Adjust. Method	Switch Type	Power Good Signal	Synchronous Switching	Shutdown Mode	Shutdown Mode	DC-DC Outputs	Oper. Freq. (kHz)	Design Tools	Package/Pins
	min	max	min	max							Current (μA)	Current (μA)				
MAX20472	3	4	4.5	5.5	5	1	Preset	Internal	Yes	Yes	0.1	2	1	2200	EE-Sim	TDFN-CU/12
MAX20471						-										SOIC (N)/8 TDFN-CU/12

[See All Step-Up Switching Regulators \(98\)](#)